

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15PX601SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15PX601SN1%23

"#" indicates a package specification code.

In Production RoHS REACH

BLM15PX601SN1#

< List of part numbers with package codes > BLM15PX601SN1B BLM15PX601SN1D BLM15P

BLM15PX601SN1J



Appearance & Shape



| 0.25±0.1 | |
|----------|----------|
| | |
| 1.0±0.05 | 0.5±0.05 |
| | |



0.5±0.05

Packaging Information

| Packaging | Specifications | Standard Packing Quantity |
|-----------|------------------|---------------------------------|
| В | Bulk(Bag) | 1000 |
| D | 180mm Paper Tape | 10000 |
| J | 330mm Paper Tape | 50000 |

Applications

Other Usage

For general

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Product Search Data Sheet

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15PX601SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15PX601SN1%23

"#" indicates a package specification code.



Features

BLM15PX601SN1#

- 1. The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.
- 2. The nickel barrier structure of the external electrodes provides excellent solder heat resistance. 3.BLM_P series can be used in high current circuits
- due to its low DC resistance. It can match power lines to a maximum of 6ADC.

2 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





BLM15PX601SN1#

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15PX601SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15PX601SN1%23

"#" indicates a package specification code.



Specifications

| Shape | SMD |
|------------------------------------|----------------|
| Size Code (in inch) | 0402 |
| Length | 1.0mm |
| Length Tolerance | ±0.05mm |
| Width | 0.5mm |
| Width Tolerance | ±0.05mm |
| Thickness | 0.5mm |
| Thickness Tolerance | ±0.05mm |
| Operating Temperature Range | -55°C to 125°C |
| Mass(typ.) | 0.001g |
| Number of Circuit | 1 |
| Rated Current (at 85°C) | 900mA |
| Rated Current (at 125°C) | 500mA |
| DC Resistance(max.) | 0.23Ω |
| Impedance (at 100MHz) | 600Ω |
| Impedance (at 100MHz) Tolerance | ±25% |
| Size Code (in mm) | 1005 |

3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.




Note: This datasheet may be out of date. Please download the latest datasheet of BLM15PX601SN1# from the official website of Murata Manufacturing Co., Ltd. http://www.murata.com/en/products/productdetail?partno=BLM15PX601SN1%23

"#" indicates a package specification code.

Product Data


BLM15PX601SN1#



Impedance-Frequency Characteristics

In operating temperature exceeding +85°C, derating of current is necessary for BLM15PX series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Derating of Rated Current

(Resistance element becomes dominant at high frequencies.)

Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

